



Firmware Release Notes

Advanced Line Switch

IE-SW-AL26M-22GTPOE-2GCPOE-2GESFP (Article No. 3109780000)

Attention: Before commissioning the device for the first time, we strongly recommend checking the installed firmware version and updating to the latest version, if a newer one is available for download from the Weidmüller website.

For information on bug fixes, implementation of new functions and other adjustments to previously released firmware versions, please read below release notes carefully.

After updating the device at **first** commissioning (having still initial factory default settings) to the latest firmware, we strongly recommend performing a reset to factory defaults additionally after the new firmware is running.

Version 2.02 (IEC 62443-4-2 compliant)

Release Date: September 16, 2026

Note: This version is the first firmware compliant to cybersecurity requirements according to IEC 62443-4-2 SL1.

Regarding aspects to consider when upgrading from any non-cybersecure firmware (V1.xx) to an IEC 62443-compliant version (V2.xx), or when downgrading from a cybersecure version to a non-cybersecure one, please refer to document “Info_Upgrade_to_IEC62443-compliant_Firmware_V2.02.pdf” (attached to downloadable firmware file).

New Cybersecurity Features according to IEC 62443-4-2 SL1:

- Added mandatory administrator password setup on first login.
 - After upgrade, from any non-cybersecure version V1.xx a password change will be required at first login if current password is the factory default one.
- Added configurable password policy settings.
- Added role-based user and group management.
- Added account lockout protection.
- Added audit logging functionality.
- Added automatic logout for inactive sessions.
- Added session-based web authentication and concurrent login control.
- Added pre-login security banner support.
- Added password expiration reminder mechanism.
- Enabled HTTPS, SSH, LLDP and PROFINET by default while disabling non-essential services.
- Added dedicated flash storage for audit logs.
- Enhanced audit log integrity verification and traceability.
- Added SHA-256 integrity validation for security-related data.
- Added SHA-256 integrity protection for the bootloader and critical data partitions.

Feature Enhancements / Updates:

- Switch models running firmware version 2.02 can be maintained in Weidmüller network management software “u-netops”.

Bug Fixes:

- Fix regarding DHCP Server function when configuring several DHCP pools each with a unique VLAN. This did not work because the DHCP Server could only be accessed via the management VLAN ID. If the management VLAN ID was different to the VLAN ID of a DHCP pool, then no DHCP setting for clients was possible.

Version 1.37

Release Date: November 27, 2025

Feature Enhancements / Updates:

- Adaption of internal storage format of running and startup configuration (Flash Memory). This requires an additional saving of the configuration immediately after firmware update from a version <= V1.35 to version V1.37. An information message is displayed as a hint for the user when the switch comes up again with new firmware after the reboot process. The note will be displayed for both procedures of firmware update, via Web interface as well as for the command line interface (CLI).
 - *Note Web GUI:* The internal format for saving the configuration data has been changed with this firmware update and requires the running configuration to be saved as startup configuration again. To avoid losing the current configuration, go to webpage "Save/Manage Configuration" and press button "Save as Startup Configuration".
 - *Note CLI:* Attention: The internal format for saving the configuration data has been changed with this firmware update and requires the running configuration to be saved as startup configuration again. To avoid losing the current configuration, apply command 'copy running-config startup-config' now.
- Improvement of the command line interface (CLI):
 - Support of RADIUS and TACACS+ options 'unencrypted' and 'encrypted' for parameter 'key'. The commands have been adapted as below described:
 - radius-server key { [unencrypted] <unencrypted_key> | encrypted <encrypted_key> }
 - tacacs-server key { [unencrypted] <unencrypted_key> | encrypted <encrypted_key> }
 - radius-server host <host_name> [auth-port <auth_port>] [acct-port <acct_port>] [timeout <seconds>] [retransmit <retries>] [key { [unencrypted] <unencrypted_key> | encrypted <encrypted_key> }]
 - tacacs-server host <host_name> [port <port>] [timeout <seconds>] [key { [unencrypted] <unencrypted_key> | encrypted <encrypted_key> }]

Note: <Unencrypted_key> is a readable plain text. <Encrypted_key> is the encrypted hash-code of readable plain-text. The hash-code can be seen in the configuration backup file (e.g. created via Web interface) if RADIUS respectively TACACS+ have been configured.
 - New command 'configuration paste' implemented to be used for pasting a complete configuration command sequence as one step.
 - Short information about the procedure: Copy the text-based content of a backup file, establish a CLI session, and enter command 'configuration paste'. Then paste the copied data into the command line.
 - When using a SSH connection via PuTTY now the backspace key works out of the box. Previously for deleting a character the key sequence 'Strg + H' must be entered.
- Improvement SNMP related features:
 - Menu 'SNMP → Trap → Section Events': Implementation of new SNMP trap events on configuration changes.
 - Support of new private OIDs to query CPU and memory status via section 'switchInfoTable'.
 - **Note:** Needs downloadable device specific private MIB file dated from 2025-11-26 or later.
 - Support of OID 1.3.6.1.2.1.2.2 (Standard MIB-2 → Section 'interfaces' → ifTable → ifAdminStatus) allowing port disabling and enabling.
 - Support of OID 1.3.6.1.2.1.3.1 (Standard MIB-2 → Section 'at' → atTable) allowing to retrieve the address translation table.
 - Adaption of OID 1.3.6.1.2.1.17.1.4.1.2.1 (Standard MIB-2 → Section dot1dBridge' → dot1dBase → dot1dBasePortTable → dot1dBasePortIndex) which now shows the retrieved port numbers beginning from number 1. Previously the numbering of the port interface index has started from 1000001, 1000002, 1000003, etc.

Bug Fixes:

- Weidmüller Gigabit SFP transceiver IE-SFP-1GE-RJ45 (Article No.2766120000) could not establish a link to Fast Ethernet devices being only capable to run at 100 Mbit/s.
- Adaptions related to RADIUS and TACACS+ configuration:
 - When upgrading from firmware **V1.31 or previous version** to **V1.33 or V1.35** the RADIUS and TACACS+ configuration settings were deleted. This was caused by changing the storing mechanism of RADIUS and TACACS+ server keys. Due to security requirements the server keys have been stored since version V1.33 as encrypted hash-code while in the older versions the keys were stored as readable plain-text both in the flash memory and in the backup file.
 - An upgrade from firmware **V1.31 or previous version** to **V1.37 or a newer version** no longer causes any problem, the configured RADIUS and TACACS+ settings are adopted correctly. During update process the RADIUS/TACACS+ keys stored as readable plain-text are converted to encrypted hash-code.

- **Attention:** Due to change of key storing above described an upgrade from firmware V1.33 or V1.35 to V1.37 or a newer version still causes the problem, that configured RADIUS and TACACS+ key settings are interpreted wrongly.
 - The reason is that for V1.33/1.35-based startup configurations the keys already are stored as encrypted hash-code but are not saved with key option 'Encrypted'. However, V1.37 or a newer version expects - when upgrading - either key option 'Encrypted' or 'Unencrypted' to interpret a stored key correctly. If no key option is found, then the key will be handled as plain text. Resulting, at update process the encrypted hash-code in the startup configuration will be encrypted again and stored as supposedly encrypted plain text. This can be recognized, that after update on Web pages 'RADIUS Server Configuration' and 'TACACS Server Configuration' the de-crypted key of the twice encrypted hash-code will be shown (which is the original hash-code before it was encrypted again).
 - Resulting, after update from firmware V1.33 or V1.35 to V1.37 or a newer version the RADIUS/TACACS+ server keys are corrupted and must be re-entered manually.

Version 1.35

Release Date: June 30, 2025

- This is the initial firmware version at market launch!